

Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 939 508 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
01.09.1999 Bulletin 1999/35

(51) Int Cl. H04J 11/00, H04B 7/26

(21) Application number: 99301134.5

(22) Date of filing: 16.02.1999

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

• Mallender, Laurence Eugene
Hoboken, New Jersey 07030 (US)
• Yeh, Yu Shuan
Freehold, New Jersey 07726 (US)

(30) Priority: 27.02.1998 US 32166

(71) Applicant: LUCENT TECHNOLOGIES INC,
Murray Hill, New Jersey 07974-0636 (US)

(74) Representative:
Buckley, Christopher Simon Thirak et al
Lucent Technologies (UK) Ltd,
5 Morningside Road
Woodford Green, Essex IG8 0TU (GB)

(72) Inventors:
• Gans, Michael James
Holmdel, New Jersey 07733 (US)

(54) Method and apparatus for achieving data rate variability in orthogonal spread spectrum communications systems

(57) A CDMA communication system is disclosed offering a near continuum of data rates up to a maximum rate. The disclosed CDMA communication system increases the data rate variability, without disturbing the orthogonality between users. An increased number of data rates is obtained by time multiplexing the data rates achievable with conventional CDMA systems to provide additional data rates for various multimedia applications. If a user is assigned a specific orthogonal code sequence, such as a Walsh sequence, which permits a maximum data rate, nR , with conventional systems, the user can obtain additional desired data rates up to the maximum rate nR , by time multiplexing the specific orthogonal code set. Desired bit rates are achievable for applications requiring bit rates that are not an integer multiple of the rates provided by conventional techniques. A fundamental rate of R or "fat pipe" rates of powers-of-two multiples of the fundamental rate can be achieved in a conventional man-

ner. A desired rate up to the maximum "fat pipe" rate is achieved by time multiplexing the codes w_k^1 to achieve rates between R and nR , where w_k^1 denotes the first n th of the spread spectrum code w_k . The transmitter of the present invention achieves a rate conversion to match the appropriate codeword to the appropriate data rate, by employing buffering and reclocking of the data, with time multiplexing of the orthogonal Walsh codes corresponding to the available lower and upper rates. The rate conversion must be synchronized with the selection of the orthogonal Walsh code (corresponding to the lower and upper rates)




FIG. 6

EP 0 939 508 A2

EP 0 939 508 A2

Description

Field of the Invention

[0001] The present invention relates to cellular and other communication systems, and more particularly, to methods and apparatus for achieving additional data rates in communication systems utilizing code division multiple access (CDMA).

Background of the Invention

[0002] When multiple users share a transmission medium, some form of multiplexing is required to provide separable user sub-channels. There are many multiplexing techniques available which simultaneously transmit information signals within the available bandwidth, while still maintaining the quality and intelligibility that are required for a given application. Code division multiple access (CDMA) techniques, for example, transmit multiple information signals on the same channel, and differentiate each user sub-channel by encoding it with a unique spreading code.

[0003] Code division multiple access (CDMA) techniques have been employed in many digital wireless communication systems to permit a large number of system users to communicate with one another. Current CDMA networks were designed to carry only voice traffic and exhibit limited data rate variability. CDMA networks, however, must evolve to encompass a variety of multimedia applications, each having potentially different data rates. Thus, CDMA networks will be required to carry information associated with the various multimedia applications at various data rates, corresponding to the requirements of diverse wireless services demanded by customers.

[0004] Many communication systems utilizing code division multiple access (CDMA) comply with the IS-95 standard, adopted by the Telecommunication Industry Association (TIA). Under the IS-95 standard, a communication system substantially eliminates co-channel interference and improves the bit energy-to-noise density ratio, E_b/N_0 , on the forward link from a base station or cell site to a mobile receiver unit by modulating the information signals with Walsh orthogonal function sequences. To produce corresponding orthogonal information signals, these CDMA systems require that the forward link information signals be transmitted in a synchronized manner. A more detailed discussion of the IS-95 standard is provided in "Mobile Station-Base Station Compatibility Standard for Dual-Mode Wideband Spread Spectrum Cellular System," Telecommunication Industry Association Doc. No. TIA/EIA/IS-95 (1993), incorporated by reference herein.

[0005] Current implementations of the IS-95 standard, however, allow only a limited number of data rates. Specifically, the Telecommunication Industry Association has recently adopted a new standard, IS-95B, for increasing the data rates that may be achieved with CDMA networks. The IS-95B standard, however, only permits data rates that are integer or power-of-two multiples of the basic CDMA rate. While such techniques satisfy the data rate needs of many applications, the utility of CDMA networks could be significantly extended if further data rate variability could be achieved.

Summary of the Invention

[0006] Generally, a CDMA communication system offering a near continuum of data rates up to a maximum rate is disclosed. The disclosed CDMA communication system increases the data rate variability, without disturbing the orthogonality between users. An increased number of data rates is obtained by time multiplexing the data rates achievable with conventional CDMA systems to provide additional data rates for various multimedia applications.

[0007] In accordance with one feature of the present invention, if a user is assigned a specific orthogonal code sequence, such as a Walsh sequence, which permits a nominal data rate, R , and higher data rates, nR , the user can obtain additional desired data rates by time multiplexing the specific orthogonal code set. In this manner, desired bit rates are provided for applications requiring bit rates that are not an integer multiple of the rates provided by conventional "lat pipe" techniques.

[0008] In an illustrative sixteen dimension implementation, if a specific code quadruple, such as the code quadruple $(w_k, w_{k+4}, w_{k+8}, w_{k+12})$ ($k=0, 1, 2, 3$), is assigned to an information source, any rate can be achieved, up to a rate of $4R$. Rates R , $2R$, $4R$ and $16R$ can be achieved by assigning other appropriate code sets to the information source, in a conventional manner. According to a feature of the invention, any desired rate up to $4R$ is achieved by time multiplexing the codes w_k , w_{k+4} and w_{k+8} . The symbol, w_k^n , denotes the first n th of the spread spectrum code w_k (hence, $n=2$ denotes the first half of the sequence). Thus, the user can achieve any data rate that is a rational scale factor combination of the rates R and $4R$.

[0009] The transmitter of the present invention achieves a rate conversion to match the appropriate codeword to the appropriate data rate, by employing buffering and relocking of the data, with time multiplexing of the orthogonal Walsh codes corresponding to the available lower and upper rates. The rate conversion must be synchronized with the se-

EP 0 939 508 A2

fraction of the orthogonal Walsh code (corresponding to the lower and upper rates). For example, an application requiring a data rate between 2R and 4R, such as 2.3R, would require multiplexing of the 2R and 4R Walsh codes ($w_k^{(2)}$ and $w_k^{(4)}$) to achieve the desired 2.3R rate. If the 2.3R application was assigned the specific code quadruple (w_1, w_5, w_9, w_{13}), the sequence $w_1^{(2)}$ is utilized to achieve a rate of 2R and the sequence $w_1^{(4)}$ is utilized to achieve a rate of 4R, with an appropriate balance to achieve an overall 2.3R rate, and the codes w_5, w_9, w_{13} are excluded from use.

Brief Description of the Drawings

[0010]

FIG. 1 is a block diagram of a conventional CDMA transmitter that provides user streams (or sub-channels) at a single data rate.

FIG. 2 is a table of an illustrative set of orthogonal spread spectrum codes, w_0 through w_{15} .

FIG. 3 is a block diagram of a conventional CDMA transmitter that provides at least one information signal at an integer multiple of the data rate of FIG. 1.

FIG. 4 is a block diagram of a conventional CDMA transmitter that provides at least one information signal at two times the data rate of FIG. 1.

FIG. 5 is a block diagram of a conventional CDMA transmitter that transmits at least one information signal at four times the data rate of FIG. 1.

FIG. 6 is a block diagram of one sub-channel of a CDMA transmitter offering data rate variability in accordance with one embodiment of the present invention.

FIG. 7 is a block diagram of one embodiment of the rate converter of FIG. 6; and

FIG. 8 is a block diagram of a CDMA receiver offering data rate variability in accordance with one embodiment of the present invention.

Detailed Description

[0011] The present invention relates to a method and apparatus for modulating a communication signal in a code division multiple access (CDMA) environment using orthogonal spread spectrum codes. As discussed further below in conjunction with FIGS. 1 through 3, conventional CDMA spread spectrum modulation techniques with orthogonal codes only permit data rates that are integer or power-of-two multiples of the chip rate. The present invention improves on conventional CDMA spread spectrum modulation techniques by time multiplexing the data rates achievable with conventional CDMA systems to provide additional data rates for various multimedia applications. In one preferred embodiment, a continuum of data rates are provided.

[0012] As previously indicated, it is often desirable to differentiate a number of information signals transmitted on the same carrier frequency with unique orthogonal spread spectrum codes. This is typically accomplished by encoding each bit to be transmitted using a predefined codeword, or pattern, consisting of n "chips" or "signal elements." In standard antipodal encoding, the predefined codeword may be utilized to represent a value of binary "0" and the inverse of the predefined codeword may be utilized to represent a value of binary "1."

[0013] A number of orthogonal spread spectrum codes, consisting of a number of consecutive positive and negative signal elements, such as Walsh codes, have been discovered which have unique properties that optimize the detection of the transmitted information. Under the IS-95 standard for CDMA networks, for example, sixty-four different Walsh codewords, w_0 through w_{63} , each consisting of sixty-four chips, permit 64 different information signals to be transmitted on the same carrier frequency. Since a number of channels are reserved for administration, such as the pilot, synchronizing and paging channels, less than the available sixty-four channels typically transmit user information.

[0014] In the illustrative embodiment discussed herein, sixteen different Walsh codewords, w_0 through w_{15} , each consisting of sixteen chips, permit up to sixteen different information signals, d_0 through d_{15} , to be transmitted on the same carrier frequency. Thus, as shown in FIG. 1, in order to transmit data on the downlink portion of a conventional CDMA system from one or more information sources, such as sources 101-116, to a plurality of end users, such as end users 181-196, a transmitter 100 encodes each of sixteen data streams, d_0 through d_{15} , to be transmitted using one of sixteen different Walsh codewords, w_0 through w_{15} . The illustrative Walsh codewords, w_0 through w_{15} , are

EP 0 939 508 A2

shown in FIG. 2. The encoded signals will then be combined and modulated in a conventional manner, prior to transmission over a transmission medium 130. The transmission medium 130 may be embodied as a conventional or wireless communications network. The modulator may employ a modulation technique, for example, which multiplies the codeword by a sinusoidal carrier wave in order to shift the signal frequency upward to the carrier frequency (not shown). In this manner, the original signal spectrum may be translated into a particular frequency band allocated by the Federal Communications Commission (FCC) or another regulatory body.

[0015] Upon receipt of the transmitted signal by the receiver 150, the frequency of the received signal is typically first shifted down (not shown) to the base band by a demodulator, thus returning the signal to its original form prior to modulation. Thereafter, the received signal is passed through a series of filters, such as filters 161-170, that are each matched to the characteristics of the appropriate codeword, w_0 through w_{15} . It is noted that the receiver 150 may be associated with all sixteen end users 181 through 196, as shown in FIG. 1. More typically, however, each end user, such as end user 181, will have its own receiver 150. For a more detailed discussion of a prior art CDMA communication system, see U.S. Patent No. 4,901,307, incorporated by reference herein.

[0016] For the transmitter 100 shown in FIG. 1, each of the information sources 101-116 transmits at a uniform rate, R , and the symbol duration is equal to the Walsh code duration. Additional data rate variability can be achieved within the implementation shown in FIG. 1, by assigning multiple orthogonal spread spectrum codes, such as Walsh codes, to the same high rate information source, such as the source 101. For example, in order to achieve a transmission rate, such as $3R$, for a single source 101, three Walsh codewords (sub-channels) can be assigned to the information source 101. Thus, the set of achievable data rates are integer multiples of the symbol rate, R . As shown in FIG. 3, multicoded source 101 will require additional buffering, typically in the form of a serial-to-parallel converter 310. It is noted that the transmitter 100 shown in FIG. 3 can combine any of the sixteen sub-channels associated with the codewords, w_0 through w_{15} , to increase the data rate for a single information source 101 to a maximum of $16R$.

[0017] A second well-known method for increasing the transmission rate in a code division multiple access (CDMA) network, commonly referred to as the "fat pipe" method, "punctures" the set of illustrative Walsh codes shown in FIG. 2. As discussed below, the "fat pipe" method achieves data rates that are power-of-two multipliers of the chip rate, without requiring buffering of the multiple rate user. In other words, the achievable data rates are R , $2R$, $4R$, $8R$ and $16R$ (for the illustrative 16 dimensional Walsh codes shown in FIG. 2). Specific code pairs, such as the code pairs (w_0 , w_8) or (w_1 , w_9), are assigned to the double rate users, transmitting at rate $2R$. Each double rate user, however, will encode data with only the first half of one of the assigned orthogonal spread spectrum codes. The symbol, w_k^1 , denotes the first half of the spread spectrum code w_k shown in FIG. 2. Thus, as shown in FIG. 4, for the spread spectrum code pair, (w_1 , w_9) assigned to the information source 410, w_1^1 is utilized to encode data at a rate of $2R$, and w_9 is excluded from use by all information sources. It is noted that for each pair (w_k , w_{k+8}), $w_{k+8}^1 = w_k^1$, and the second half of the spread spectrum code w_{k+8} is the opposite polarity of the spread spectrum code w_k .

[0018] Likewise, specific code quadruples, such as the code quadruple (w_0 , w_4 , w_8 , w_{12}) or (w_1 , w_5 , w_9 , w_{13}), are assigned to each quadruple rate user, transmitting at a rate $4R$. Thus, as shown in FIG. 5, for the orthogonal spread spectrum code quadruple (w_0 , w_4 , w_8 , w_{12}) assigned to an information source 510, w_0 is utilized to encode data and w_4 , w_8 , and w_{12} are excluded from use by all information sources. Similarly, for the spread spectrum code quadruple (w_1 , w_5 , w_9 , w_{13}) assigned to an information source 520, w_1 is utilized to encode data and w_5 , w_9 , and w_{13} are excluded from use by all information sources. The symbol, w_k^2 , denotes the first quarter of the spread spectrum code w_k shown in FIG. 2. It is noted that for each code quadruple (w_k , w_{k+4} , w_{k+8} , w_{k+12}), $w_{k+12}^2 = w_{k+8}^2 = w_{k+4}^2 = w_k^2$, and the last three-quarters of each spread spectrum code w_{k+4} , w_{k+8} , w_{k+12} is the same or opposite polarity of the spread spectrum code w_k . It is further noted that the "fat pipe" method does not require buffering of the higher rate users, the codes are not summed, and the signal's peak-to-average ratio is not increased.

[0019] According to a feature of the present invention, additional data rates are achieved while maintaining the orthogonal signal structure discussed above for conventional code division multiple access (CDMA) transmitters. In accordance with the present invention, if a user is assigned a specific code set in the manner described above, which permits a maximum data rate nR , the user can obtain additional desired data rates up to the maximum rate nR , by time multiplexing the specific code set. In order to achieve a non-integer rate with conventional systems, however, such as a rate of $2.5R$, conventional techniques would require "dummy" data, such as all zeros, to be added to the transmitted stream to bring the presented rate up to the next greatest available "fat pipe" rate, such as $4R$. Thus, the present invention provides desired bit rates for applications that have a bit rate that is not an integer multiple of the rates provided by the "fat pipe" technique discussed above.

[0020] For example, if a specific code quadruple, (w_k , w_{k+4} , w_{k+8} , w_{k+12}) ($k=0, 1, 2, 3$), is assigned to an information source 610, any rate can be achieved, up to a rate of $4R$. While the user can achieve a fundamental rate of R in the manner described above in conjunction with FIG. 1 by employing the spread spectrum code w_0 , a "fat pipe" rate of $2R$ in the manner described above in conjunction with FIG. 4 by employing the spread spectrum code w_0^2 , or a "fat pipe" rate of $4R$ in the manner described above in conjunction with FIG. 5 by employing the spread spectrum code w_0^4 and the present invention, the user can achieve desired additional lower rates by time multiplexing the codes w_0 , w_0^2 and

EP 0 939 508 A2

w_0^4 , to achieve rates between R and $4R$. In other words, the user can achieve any data rate that is a rational scale factor combination of the rates R and $4R$.

[0021] As shown in FIG. 6, the transmitter 600 of the present invention achieves a rate conversion by employing buffering and reclocking of the data, with time multiplexing of the orthogonal Walsh codes corresponding to the available lower and upper rates. As discussed further below, the rate conversion must be synchronized with the selection of the orthogonal Walsh code (corresponding to the lower and upper rates). For example, the illustrative $2.3R$ application would require multiplexing of the $2R$ and $4R$ Walsh codes to achieve the desired $2.3R$ rate. If the $2.3R$ application was assigned the specific code quadruple (w_1, w_5, w_9, w_{13}) , the sequence w_1^4 is utilized to achieve a rate of $4R$, and the codes w_5, w_9, w_{13} are excluded from use.

[0022] Thus, when the high rate service is requested, by either the mobile terminal (and user) or the base station (information source), the sync channel (or another administration channel) is preferably utilized to coordinate the wireless service. The originating entity will send a message either requesting or confirming the rate, as well as the particular codes desired. For example, if the mobile terminal requests a channel having a $2.3R$ rate, the base station will grant or deny the request, and supply the assigned sequences, if available. In one preferred embodiment, the base station will supply the mobile terminal with the assigned sequences, as well as the amount of data that should be transmitted at each of the lower and upper rates. Thus, the sync channel protocol may consist of a message containing a user identifier (indicating, for example, the mobile terminal), a sequence number (indicating the particular Walsh code, w_0 through w_{15} , to utilize), the number of repetitions, N_L and N_U , and the rate exponents, R_L and R_U , for the lower and upper rates, respectively (such as $2R$, $4R$, or $8R$). Thus, from the sequence number and the upper rate, R_U , the mobile terminal knows which other sequences must be excluded.

[0023] The number of repetitions, N_L and N_U , is the number of symbols to transmit at each of the lower and upper rates, respectively. The number of repetitions is determined by the following equation:

$$R_{\text{final}} = \left[\frac{R_L R_U (N_L + N_U)}{N_L R_U + N_U R_L} \right] R$$

where R_{final} is the desired rate to be achieved and R is the fundamental rate. Thus, to achieve a desired rate of $2.3R$, $R_L = 2$ and $R_U = 4$, one solution is $N_L = 17$ and $N_U = 6$. One method for determining this solution recognizes that 2.3 can be written as a ratio of the integers 23 and 10 . Writing R_{final} as this ratio, and using the above equation, leads to a system of linear equations:

$$4N_L + 4N_U = 23n$$

$$2N_L + N_U = 10n,$$

where n is an arbitrary integer. These equations can be solved repeatedly for $n = 1, 2, 3, \dots$ until a solution is found for which N_L and N_U are both integers.

[0024] Thus, as shown in FIG. 6, the transmitter 600 of the present invention includes a rate converter 620 and a clock 630 to buffer and reclock the data, respectively, received from a high rate source 610. The rate converter 620 must be synchronized with the selection of the orthogonal Walsh code (corresponding to the lower and upper rates), w_k^L and w_k^U by a switch 640. The output of the rate converter 620 exhibits two different bit durations, and the Walsh codes, w_k^L and w_k^U , are used accordingly to multiply the data by a multiplier 650. Thus, the information source has been matched to the existing bit pipe rates.

[0025] FIG. 7 illustrates one implementation of the rate converter 620. Thus, the rate converter 620 includes two buffers 710 and 720. The first buffer 710 fills with data at a constant rate, and the second buffer 720 is read by an asymmetric multiplexer 730 for every $(N_L + N_U)$ bits. Thus, for the $2.3R$ example discussed above, 17 bits (N_L) are read out of the buffer 720 at a rate of $2R$ (R_L) and the last 6 bits (N_U) are read out of the buffer 720 at a rate of $4R$ (R_U). Thus, the clock at the input of the buffer 710 is symmetric (evenly spaced), while the clock at the output of the asymmetric multiplexer 730 is asymmetric. The clock 630 controls the buffer 720, the asymmetric multiplexer 730 and the selection of the Walsh code by the switch 640 for the multiplier 650.

[0026] FIG. 8 illustrates one implementation of a receiver 800 in accordance with the present invention. The receiver 800 includes a multiplier 810, which selectively multiplies the received data by the appropriate Walsh code, as selected

EP 0 939 508 A2

by a switch 820 an integrate, dump, detect block 830 for determining the received bit polarities, a rate converter 840 and a clock 950. The rate converter 840 operates in a similar manner to the rate converter 620, discussed above in conjunction with FIGS. 6 and 7. The selection of the low rate or upper rate Walsh waveform at the multiplier 810 is tied to the integrator 830 and the input clock of the rate converter 840. In the receiver 800, the input clock of the rate converter 840 is asymmetric while the output clock is symmetric.

[0027] It is to be understood that the embodiments and variations shown and described herein are merely illustrative of the principles of this invention and that various modifications may be implemented by those skilled in the art without departing from the scope and spirit of the invention.

Claims

1. A method of transmitting spread spectrum signals in a communication system, said method comprising the steps of:

encoding a data signal with a first and a second orthogonal function sequence to form a spread signal, wherein said first orthogonal function produces a first spread signal at a first rate and said second orthogonal function produces a second spread signal at a second rate; and

combining said first and second spread signal to produce a combined spread signal having a data rate between said first and second rates.

2. The method according to claim 1, wherein said combining step further comprises the step of converting the rate of said data signal to said first and second rates.

3. A spread spectrum communication system for transmitting a data signal comprising:

an orthogonal function encoder that combines a data signal with at least a first and a second orthogonal function sequence to form a spread signal, wherein said first orthogonal function produces a first spread signal at a first rate and said second orthogonal function produces a second spread signal at a second rate; and

means for combining said first and second spread signal to produce a combined spread signal having a data rate between said first and second rates.

4. The transmitter according to claim 3, wherein said orthogonal function encoder converts the rate of said data signal to said first and second rates.

5. The transmitter according to claim 4, wherein said orthogonal function encoder includes a rate converter for buffering and reclocking said data signal and time multiplexing said orthogonal function sequences corresponding to said first and second rates.

6. The transmitter according to claim 3, further comprising means for transmitting with said combined spread signal an indication of said first and second orthogonal function sequences, said first and second rates and the amount of data transmitted at each of said first and second rates.

7. A method for receiving spread spectrum signals at a transmission rate in a communication system comprising

decoding said received spread spectrum signal with at least a first and a second orthogonal function sequence to produce a combined digital signal, wherein said first orthogonal function sequence produces a first digital signal at a first rate and said second orthogonal function sequence produces a second digital signal at a second rate, wherein said transmission rate is between said first rate and said second rate; and

detecting a data signal in said combined digital signal.

8. The method according to claim 7, wherein said decoding step further comprises the step of converting the rate of said data signal to said first and second rates.

9. The method according to claim 8, wherein said converting step consists of buffering and reclocking said data signal and time multiplexing said orthogonal function sequences corresponding to said first and second rates.

EP 0 939 508 A2

10. The method according to claim 7, further comprising the step of receiving with said spread spectrum signal an indication of said first and second orthogonal function sequences, said first and second rates and the amount of data transmitted at each of said first and second rates

11. A method of transmitting a data signal in a spread spectrum communication system, said method comprising the steps of:

encoding a portion of said data signal with a first orthogonal function sequence to form a first spread signal at a first rate;

encoding a remaining portion of said data signal with a second orthogonal function sequence to form a second spread signal at a second rate; and

time multiplexing said first and second spread signals to achieve a combined spread signal at a desired rate between said first rate and said second rate

12. The method according to claim 11, wherein said encoding steps further comprise the step of converting the rate of said data signal portions to said first and second rates

13. The method according to claim 2 or 12, wherein said converting steps consist of buffering and re-clocking said data signal and time multiplexing said orthogonal function sequences corresponding to said first and second rates.

14. The method according to claim 1 or 11, further comprising the step of transmitting with said combined spread signal an indication of said first and second orthogonal function sequences, said first and second rates and the amount of data transmitted at each of said first and second rates.

15. A receiver for receiving spread spectrum signals at a transmission rate in a communication system comprising:

an orthogonal function decoder that combines said received spread spectrum signal with at least a first and a second orthogonal function sequence to produce a combined digital signal, wherein said first orthogonal function sequence produces a first digital signal at a first rate and said second orthogonal function sequence produces a second digital signal at a second rate, wherein said transmission rate is between said first rate and said second rate, and

a processor for detecting a data signal in said combined digital signal.

16. The receiver according to claim 15, wherein said orthogonal function decoder converts the rate of said data signal to said first and second rates.

17. The receiver according to claim 15, wherein said orthogonal function decoder includes a rate converter for buffering and re-clocking said data signal and time multiplexing said orthogonal function sequences corresponding to said first and second rates.

18. The receiver according to claim 15, further comprising means for receiving with said spread spectrum signal an indication of said first and second orthogonal function sequences, said first and second rates and the amount of data transmitted at each of said first and second rates.

19. A method of transmitting spread spectrum signals at a desired rate in a communication system, said method comprising the steps of:

encoding a data signal with at least a first and a second orthogonal function sequence to form a combined spread signal, wherein said first orthogonal function produces a first spread signal at a first rate and said second orthogonal function produces a second spread signal at a second rate,

combining said first and second spread signal to produce a combined spread signal having a data rate between said first and second rates, and

determining the proportion of said data in said combined spread signal at said first and second rates.

EP 0 939 508 A2

20. The method according to claim 18, wherein said determining step further comprises the step of solving the following equation to determine the number of symbols, N_L , to transmit at said first rate, R_L , and the number of symbols, N_U , to transmit at said second rate, R_U , in order to achieve said desired rate, R_{total} .

$$R_{total} = \left[\frac{R_L R_U (N_L + N_U)}{N_L R_U + N_U R_L} \right] R$$

21. A method of transmitting spread spectrum signals in a communication system, said method comprising the steps of

encoding a data signal with a first and a second orthogonal function sequence to form a spread signal, wherein said first orthogonal function produces a first spread signal at a first rate and said second orthogonal function produces a second spread signal at a second rate; and

time multiplexing said first and second spread signal to produce a multiplexed spread signal having a data rate between said first and second rates.

22. The method according to claim 21, wherein said time multiplexing step maintains said orthogonality

23. A method of transmitting spread spectrum signals in a communication system, said method comprising the steps of,

encoding a data signal with a first and a second orthogonal function sequence to form a spread signal, wherein said first orthogonal function produces a first spread signal at a first rate and said second orthogonal function produces a second spread signal at a second rate; and

combining said first and second spread signal to achieve a data rate that is a rational scale factor combination of said first and second rates

24. A spread spectrum data signal characterized in that a bandwidth of said spread spectrum data signal is any bandwidth that is a rational scale factor of two rates achievable by a system generating said spread spectrum data signal.

25. A spread spectrum data signal characterized in that at least a portion of a channel defined by orthogonal spreading functions and capable of achieving two data rates is time multiplexed between said two data rates.

EP 0 939 508 A2




FIG. 1
PRIOR ART

EP 0 939 508 A2

WALSH CODES

w_0 : 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1
 w_1 : 1, -1, 1, -1, 1, -1, 1, -1, 1, -1, 1, -1, 1, -1, 1, -1
 w_2 : 1, 1, -1, -1, 1, 1, -1, -1, 1, 1, -1, -1, 1, 1, -1, -1
 w_3 : 1, -1, -1, 1, 1, -1, -1, 1, 1, -1, -1, 1, 1, -1, -1, 1
 w_4 : 1, 1, 1, 1, -1, -1, -1, -1, 1, 1, 1, 1, -1, -1, -1, -1
 w_5 : 1, -1, 1, -1, -1, 1, -1, 1, 1, -1, 1, -1, -1, 1, -1, 1
 w_6 : 1, 1, -1, -1, -1, -1, 1, 1, 1, 1, -1, -1, -1, -1, 1, 1
 w_7 : 1, -1, -1, 1, -1, 1, 1, -1, 1, -1, -1, 1, -1, 1, 1, -1
 w_8 : 1, 1, 1, 1, 1, 1, 1, 1, -1, -1, -1, -1, -1, -1, -1, -1
 w_9 : 1, -1, 1, -1, 1, -1, 1, -1, -1, 1, -1, 1, -1, 1, -1, 1
 w_{10} : 1, 1, -1, -1, 1, 1, -1, -1, -1, -1, 1, 1, -1, -1, 1, 1
 w_{11} : 1, -1, -1, 1, 1, -1, -1, 1, -1, 1, 1, -1, -1, 1, 1, -1
 w_{12} : 1, 1, 1, 1, -1, -1, -1, -1, -1, -1, -1, -1, 1, 1, 1, 1
 w_{13} : 1, -1, 1, -1, -1, 1, -1, 1, -1, 1, -1, 1, 1, -1, 1, -1
 w_{14} : 1, 1, -1, -1, -1, -1, 1, 1, -1, -1, 1, 1, 1, 1, -1, -1
 w_{15} : 1, -1, -1, 1, -1, 1, 1, -1, -1, 1, 1, -1, 1, -1, -1, 1

FIG. 2

EP 0 939 508 A2




FIG. 3
PRIOR ART

EP 0 939 508 A2




FIG. 4
PRIOR ART

EP 0 939 508 A2




FIG. 5
PRIOR ART

EP 0 939 508 A2




FIG. 6




FIG. 7

EP 0 939 508 A2





FIG. 8



(11) EP 0 939 508 A3

(12)

(51) Int Cl.: H04J 11/00, H04B 7/26

(21) Application number: 99301134.5

(22) Date of filing: 16.02.1999

- Mailänder, Laurence Eugene
Hoboken, New Jersey 07030 (US)
- Yeh, Yu Shuan
Freehold, New Jersey 07728 (US)

(30) Priority: 27.02.1998 US 32166

(71) Applicant: LUCENT TECHNOLOGIES INC.
Murray Hill, New Jersey 07974-0636 (US)

(72) Inventors:
• Gans, Michael James
Holmdel, New Jersey 07733 (US)

(74) Representative:
Buckley, Christopher Simon Thirsk et al
Lucent Technologies (UK) Ltd,
5 Morningside Road
Woodford Green, Essex IG8 0TU (GB)

(54) Method and apparatus for achieving data rate variability in orthogonal spread spectrum communications systems

(57) A CDMA communication system is disclosed offering a near continuum of data rates up to a maximum rate. The disclosed CDMA communication system increases the data rate variability, without disturbing the orthogonality between users. An increased number of data rates is obtained by time multiplexing the data rates achievable with conventional CDMA systems to provide additional data rates for various multimedia applications. If a user is assigned a specific orthogonal code sequence, such as a Walsh sequence, which permits a maximum data rate, nR , with conventional systems, the user can obtain additional desired data rates up to the maximum rate nR , by time multiplexing the specific orthogonal code set. Desired bit rates are achievable for applications requiring bit rates that are not an integer multiple of the rates provided by conventional techniques. A fundamental rate of R or "fat pipe" rates of powers-of-two multiples of the fundamental rate can be

achieved in a conventional manner. A desired rate up to the maximum "bit pipe" rate is achieved by time multiplexing the codes w_k^n to achieve rates between R and nR , where w_k^n denotes the first n th of the spread spectrum code w_k . The transmitter of the present invention achieves a rate conversion to match the appropriate codeword to the appropriate data rate, by employing buffering and reclocking of the data, with time multiplexing of the orthogonal Walsh codes corresponding to the available lower and upper rates. The rate conversion must be synchronized with the selection of the orthogonal Walsh code (corresponding to the lower and upper rates).

EP 0 939 508 A3

EP 0 939 508 A3




FIG. 6

EP 0 939 508 A3

European Patent
Office

EUROPEAN SEARCH REPORT

Application Number

EP 99 30 1134

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
X	EP 0 814 581 A (NIPPON TELEGRAPH & TELEPHONE) 29 December 1997 (1997-12-29) * column 5, line 45 - column 6, line 47 * * column 9, line 41 - line 51 * * figures 1,4,5 *	1-4,7, 11-13, 15,16, 19.21-25	H04J11/00 H04B7/26
X	C-L J ET AL: "IS-95 ENHANCEMENTS FOR MULTIMEDIA SERVICES" BELL LABS TECHNICAL JOURNAL, WILEY, CA, US, vol. 1, no. 2. 21 September 1996 (1996-09-21), pages 60-87, XP000656006 ISSN: 1089-7089 * page 64, right-hand column, last paragraph - page 65, left-hand column, paragraph 1 * * page 62, left-hand column, paragraph 2 - right-hand column, paragraph 1 * * figures 1,2 *	1,3,4, 19,23-25	
A	US 5 619 491 A (PANZER HERBERT DIPL ING) 8 April 1997 (1997-04-08) * column 4, line 59 - column 5, line 12 * * column 6, line 31 - line 37 * * column 6, line 58 - column 7, line 8 *	5,9,13, 17	H04J H04L H04B
The present search report has been drawn up for all claims			
Place of search:		Date of completion of the search:	Examiner
THE HAGUE		3 February 2003	Pieper, T
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X: particularly relevant if taken alone Y: particularly relevant if combined with another document of the same category A: technological background O: non-written disclosure P: intermediate document</p> <p>T: theory or principle underlying the invention E: earlier patent document, but published on, or after the filing date D: document cited in the application L: document read for other reasons & member of the same patent family, corresponding document</p>			

EP 0 939 508 A3

ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.

EP 99 30 1134

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

03-02-2003

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 0814581 A	29-12-1997	JP 10290211 A	27-10-1998
		CA 2208085 A1	19-12-1997
		CN 1394024 A	29-01-2003
		CN 1171675 A	28-01-1998
		EP 0814581 A2	29-12-1997
		KR 254638 B1	01-05-2000
		US 6084684 A	04-07-2000
US 5619491 A	08-04-1997	DE 4319830 A1	09-03-1995
		CN 1308428 A	15-08-2001
		CN 1110890 A .8	25-10-1995
		EP 1035678 A2	13-09-2000
		EP 0659317 A1	28-06-1995
		WO 9429980 A1	22-12-1994
		JP 8503591 T	16-04-1996
		SG 44858 A1	19-12-1997

For more details about this annex, see Official Journal of the European Patent Office, No. 12/82

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☒ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.